




Questions?

For customer service please call us at 1-310-787-1100
Office Hours: 8:00 a.m. – 5:00 p.m. PST Monday-Friday
E-mail: info@eurilighting.com



LED Troffer

2 ft. x 2 ft.

2 ft. x 4 ft.

PLEASE REVIEW THE INSTRUCTIONS AND WARNINGS LISTED BELOW PRIOR TO PROPER INSTALLATION

IMPORTANT

- Read Carefully before installing the fixture. Keep these instructions for future reference.
- Thoroughly inspect the fixture for any freight damage; Freight damage should be reported to delivery carrier.
- The fixtures must be wired in accordance with the National Electrical Code and all applicable local codes. Proper grounding is required for safety.
- This product MUST be installed in accordance with the applicable installation code by an electrician familiar with the construction and operation of the product.

WARNING

- Designed for use in 120-277V 50-60 Hertz.
- RISK OF ELECTRIC SHOCK: Make sure power supply is OFF before installing or cleaning fixture. No user serviceable parts inside. Do NOT use the fixture within high humidity conditions.
- Keep away from flammable and explosive environment.
- Do NOT cover the fixture with insulation liner or similar material.
- Do NOT install where the fixture is loose or only partially supported.
- Do NOT impact or exert pressure on the fixture surface face or rear, as damage might occur.
- Suggested minimum clearance is 211mm after installation.


INSTALLATION

WIRING GUIDE


1. Wire input end of the LED driver to supply wires using connector according to wiring section. Wire connections must be insulated.
2. Connect the BLACK/BROWN lead to LINE(+) supply lead.
3. Connect the WHITE/BLUE lead to NEUTRAL/Common (-) supply lead.
4. Connect the GREEN lead to GROUND supply lead.
5. Connect PURPLE/BLUE to 0-10V SIGNAL supply lead and GREY/WHITE to 0-10V NEUTRAL/REFERENCE supply lead.

ETF22-35W103sw-2

Watt




CCT




ETF24-50W103sw-2

Watt




CCT



ADJUSTABLE CCT AND ADJUSTABLE WATT

1. Adjusting the switch, and making the switch fix on the needed Watt and CCT.
2. Adjustable watt is 2x2ft: 25W/35W, 2x4ft: 33W/40W/50W,
3. Adjustable CCT is 3000K/4000K/5000K.



HOOK INSTALLATION

1. Bring the TRCB Troffer into the T bar ceiling panel.
2. Bend T-grid ears over the top of the T bar ceiling. Fold the hook up with 90°

WIRING DIAGRAM

