Knowledge Base / Devices / Shelly BLE devices

# **Shelly BLU Button Tough 1**

### **Device image**



### **Device identification**

Device name: Shelly BLU Button Tough 1

Device model: SBBT-002C

Device Bluetooth ID: 0x0001

## **Short description**

Shelly BLU Button Tough 1 (the Device) is a smart shock, water, and dust-resistant Bluetooth button of a compact size. It features a long battery life, supports multi-click and strong encryption.

#### Main features

- Long battery life
- Shock, water, and dust-resistant
- Supports multi-click
- Compact size, portability, and ease of use
- Strong encryption

#### Use cases

- **Lighting control:** Assign a button to control specific lighting scenes or individual smart lights. For example, a single press could turn on/off the lights, while a long-term press could dim or brighten them.
- Garage door opener: Use the strong encryption of Shelly BLU Button Tough 1 and control
  your smart garage door opener as you approach or leave your garage.
- Smart blinds or curtains: Open or close motorized blinds or curtain at the touch of a button.
- Location-based automation: Set the device in Beacon mode so that to trigger specific
  actions when you come within Bluetooth range. Use the button for presence control, for
  example to keep lights on while you need to spend some time in a certain area.

## Connectivity

Bluetooth

#### **User interface**

#### **Inputs**

- One push button
  - Press and hold for 10 sec to pair ShellyBLU Button Tough 1 with another Bluetooth device.

• Press and hold for 30 sec to factory reset (possible only shortly after inserting the battery).

# **Specifications**

	∠7	
Quantity	Value	
Physical		
Size (HxWxD):	42x42x13 mm / 1.65x1.65x0.51 in	
Weight:	15 g / 0.53 oz	
Shell material:	Plastic	
Shell color:	<ul> <li>Black: C-0%; M-0%; Y-0%; K-100%</li> <li>Mocha: C-0%; M-12%; Y-28%; K-12%</li> <li>Ivory: C-3%; M-4%; Y-14%; K-8%</li> </ul>	
Environmental		
Ambient working temperature:	-20 °C to 60 °C / -5 °F to 140 °F	
Humidity:	0% to 90% RH	
Electrical		
Power supply:	1x 3 V battery (included)	
Battery type:	CR2032	
Estimated battery life:	Up to 2 years	
Bluetooth		

Protocol:	4.2
RF band:	2400 - 2483.5 MHz
Max. RF power:	< 4 dBm
Range:	Up to 30 m / 100 ft outdoors, up to 10 m / 33 ft indoors (depending on local conditions)
Encryption:	AES (CCM mode)

## **Troubleshooting**

•••

## **Components and APIs**

- This device
- All Shelly devices and services

## Compliance

• Shelly BLU Button Tough 1 multilingual EU declaration of conformity.pdf

## Battery material safety data sheet

CR-PSDS-01 Panasonic MSDS

## Printed user guide

Shelly BLU Button tough 1 multilingual printed user and safety guide.pdf

### ~372m244

Privacy policy / Cookie policy / Support / FB community support / Contact us

 $\label{lem:condition} \textbf{Copyright} @ 2024 \ \textbf{Shelly Cloud}. \ \textbf{Allterco Robotics OOD} \bullet \textbf{Powered by Scroll Viewport \& Atlassian Confluence} \bullet \\ \textbf{Reset cookie settings}$